



Fiber optic sensors

- Digital indication of sensing information
- Various advanced functions provide for optimum use of the sensor
- Unparalleled “high resolution” allows highly accurate detection
- LCD with backlight for ease of reading
- Longer detecting distance (about 2-X that of a conventional Takex model)

## Variation

Type	Model		Light source	Output mode
	NPN output	PNP output		
Digital display high-performance type	<b>F70R</b>	<b>F70RPN</b>	Red LED	Open collector (NPN/PNP)
	<b>F70G</b>	<b>F70GPN</b>	Green LED	
	<b>F70B</b>	<b>F70BPN</b>	Blue LED	
	<b>F70W</b>	<b>F70WPN</b>	White LED	


## Excellent detection performance

Built-in high-resolution provides highly accurate detection

Wide dynamic range and high resolution are achieved at the same time

High resolution is maintained even with a wide dynamic range. The provided electronic volume feature has both a wide dynamic range and high resolution.

The “electronic-volume” frequently switches the sensitivity range, each of which is divided into 1024 levels.



(6) 8-position sensing indication with electronic volume



Self-diagnosis stability indication

Function mode indicated


Operation/timer mode indicated

Light emission frequency channel switched for Anti Mutual Interference feature

## Display function :(beyond received light level)

### Displacement indication function


All amplifiers should show "0" with no work.



The value for a deviation (positive or negative) of received light level from the original level is shown at the time of detection, which allows central management of sensors.

### Absolute value indication

Received light level indication going beyond the



If the received light level at light blocking is 10 and the level at light reception is 6000, the light blocking / light reception ratio is calculated as 600 times.

supporting high resolution

### Enhanced teaching features (sensitivity setting)

- Full auto teaching

Simply pressing the button allows easy teaching of an object moving at a high speed. The teach hold feature allows indication of the maximum and minimum data.

- Auto teaching

2-point teaching with and without the presence of work, allows the detection of slight level differences such as the thickness of a piece of work and/or the presence of a film.

- Positioning teaching

This feature is ideal for high-accuracy positioning that requires accurate determination of a detecting point.

- Maximum sensitivity setting

For applications requiring a "maximum" sensitivity setting such as the detection of work with a through-beam type-fiber optic cable. The incorporated extra powerful light would allow use in an adverse environment.

- Manual setting

Arbitrary manual increase and decrease of a set-point level allows level setting while checking the operation.

### Auto sensing function compensates for adverse environment

The level of received light is constantly monitored and fluctuation is detected and automatically adjusts the activation/deactivation level.

Stable detection at optimum sensitivity is ensured even if the received light level frequently fluctuates due to dust or water drops.

### Manual hysteresis setting feature

The hysteresis can be arbitrarily set according to the application, allowing setting of a small hysteresis for severe, high-accuracy detection and a large hysteresis for detection of large variation and prevention of chattering.


### Timer functions

On-delay, off-delay and on-off delay timer functions are provided, which allows for a wide range of detecting and input conditions from the connected devices.

The delay time setting is variable between: 10 ms, 20 ms, 40 ms, 60 ms, 80 ms, 100 ms and 120 ms.

### Teach hold function

The sensor has the ability to hold instantaneous data for an object moving at a high rate of speed during full auto teaching. This data is displayed when the teaching has been completed.



(Data for light reception is 325 and for light blocking 120.)

# F70A • F70series

## Rating/Performance/Specification

Model	NPN type	F70AR	F70AG	F70AB	F70AW	F70R	F70G	F70B	F70W
	PNP type	F70ARPN	F70AGPN	F70ABPN	F70AWPN	F70RPN	F70GPN	F70BPN	F70WPN
Power supply		12-24V DC $\pm$ 10% / Ripple 10% max.							
Current consumption	NPN type	39 mA max.							
	PNP type	50 mA max.							
Output mode	Control output (*)	Open collector output / Rating: sink current 100 mA (30 VDC max.) / Residual voltage: 1 V or less							
	Stability output (*)	Open collector output / Rating: source current 100 mA (30 VDC max.) / Residual voltage: 2 V or less							
Operation mode	NPN type	Open collector output / Rating: sink current 50 mA (30 VDC max.) / Residual voltage: 1 V or less							
	PNP type	Open collector output / Rating: source current 50 mA (30 VDC max.) / Residual voltage: 2 V or less							
Operation mode		Light-ON/Dark-ON selectable							
Timer	Off delay/disabled selectable Delay time: 40 ms fixed				On delay/off delay/on-off delay/disabled selectable Delay time: selectable between 10, 20, 40, 60, 80, 100 and 120 ms / Default: 40 ms				
	Response time		Light emission frequency channel 1: 600 $\mu$ s max. Light emission frequency channel 2: 700 $\mu$ s max.				Light emission frequency channel 1: 500 $\mu$ s max. Light emission frequency channel 2: 600 $\mu$ s max.		
Light source (wavelength)		Red LED (660nm)	Green LED (525nm)	Blue LED (470nm)	White LED	Red LED (660nm)	Green LED (525nm)	Blue LED (470nm)	White LED
Indicator		Operation indicator: orange LED / Stability (STB) indicator: green LED							
Display		LCD display with backlight							
Switch		2 set buttons / Mode selector switch: RUN/SET				2 set buttons / Mode selector switch: RUN/SELECT/MODE			
Sensitivity setting		Full auto teaching / Auto teaching							
Sensitivity setting input		Set button input				Set button input/external input			
Sensitivity adjustment function		Provided (manual sensitivity adjustment)							
Functions		<ul style="list-style-type: none"> <li>• Anti Mutual Interference feature</li> <li>• Short circuit protection feature</li> </ul>				<ul style="list-style-type: none"> <li>• Sensor function: AUTO/TEACH/LOCK</li> <li>• Auxiliary function:                             <ul style="list-style-type: none"> <li>S for manual adjustment of sensitivity and activation level</li> <li>H for manual hysteresis setting</li> <li>V for displacement indication and absolute value indication modes</li> </ul> </li> <li>• Anti Mutual Interference feature</li> <li>• Self-diagnosis feature</li> <li>• Short circuit protection feature</li> </ul>			
Material		Polycarbonate							
Connection		Permanently attached cord (outer dimension: dia. 4.8) 0.2sq. 3 core 2 m length				Permanently attached cord (outer dimension: dia. 4.8) 0.2sq. 5 core 2 m length			
		For M8 connector specifications, see p. 23.							
Mass		Approx. 80 g (including 2-m cord and mounting bracket)							
Accessory		Mounting bracket / Operation manual							

(\*) Avoid the transient condition (0.5 seconds) immediately after power-up for output.

## Environmental Specification

Environment	Ambient light	Incandescent lamp: 10,000 lx / Sunlight: 20,000 lx
	Ambient temperature	1-3 adjacent units in operation: $-25 - +55$ °C
		4-10 adjacent units in operation: $-25 - +50$ °C
		11-16 adjacent units in operation: $-25 - +45$ °C Storage: $-40 - +70$ °C (non-freezing)
	Ambient humidity	35-85%RH (non-condensing)
	Protective structure	IP40
Vibration	10-55 Hz / 1.5 mm amplitude / 2 hours each in 3 direction	
Shock	500 m/s <sup>2</sup> / 3 times each in 3 directions	

代理以下品牌:

- ◇日本山武 YAMATAKE/azbil      ◇台湾阳明 FOTEK      ◇美国霍尼韦尔 HONEYWELL  
◇日本竹中 TAKEX/SEEKA ◇日本大仓 OHKURA      ◇ASEE 安圣光纤线专业生产厂  
◇日本基恩斯 KEYENCE      ◇日本理研 RIKEN 光幕/镜片◇台湾 moujen

记录仪:大仓 OHKURA, 山武 YAMATAKE      千野 CHINO,神港 SHINKO,东邦 TOHO,横河 YOKOGAWA  
安全光幕: 安圣 ASEE, SSG20 对射光幕, 神视 SUNX, 阳明 fotek, 理研 RIKEN      鲜光 SUN KWANG  
光纤放大器:山武 YAMATAKE      竹中 TAKEX      神视 SUNX,基恩斯 KEYENCE 阳明 fotek      奥托尼克斯

主营产品: 安全光幕、记录仪、光纤放大器、光纤线、接近开关、光电开关、行程开关、计数器、计时器、温控器、固态继电器、热电偶、PT100 热电阻、燃烧保护继电器、火焰检测器、PLC、变频器、触摸屏、步进电机及驱动器、各国进口品牌记录纸、色带、记录笔

欢迎访问我公司网站:[www.Lanseanet.com](http://www.Lanseanet.com)

深圳市创丰机电设备有限公司

深圳市宝安九区澎柏白金酒店商务大厦 917 室

手机:13143436561      直线: 0755-81642429

传真: 0755-61658146

联系人:钱军辉

网址 [www.Lanseanet.com](http://www.Lanseanet.com)      E-mail:sensorschina@126.com

服务 QQ:50827480      MSN:qianqun@163.com