



1kVDC Isolated 1W Dual Output DC/DC Converters




FEATURES

- RoHS compliant
- Efficiency from 81%
- Power density 0.85W/cm³
- Wide temperature performance at full
 1 Watt load, -40°C to 85°C
- UL 94V-0 package material
- No heatsink required
- Industry standard pinout
- Power sharing on output
- 5V & 12V input
- 5V, 9V, 12V, & 15V output
- Fully encapsulated with toroidal magnetics
- No external components required
- No electrolytic or tantalum capacitors

PRODUCT OVERVIEW

The MEA series is the new high performance version of our 1W NMA series. The MEA series is more efficient and offers improved regulation performance ≤5% for applications where a wide output voltage variation can not be tolerated. They are ideally suited for providing dual rail supplies with the added benefit of galvanic isolation to reduce switching noise. All of the rated power may be drawn from a single output providing the total load does not exceed 1 watt.



When operated **with** additional external load capacitance the rise time of the input voltage will determine the maximum external capacitance value for guaranteed start up. The slower the rise time of the input voltage the greater the maximum value of the additional external capacitance for reliable start up.

INPUT CHARACTERISTICS					
Parameter	Conditions	Min.	Тур.	Max.	Units
Voltage range	Continuous operation, 5V input types	4.5	5	5.5	V
	Continuous operation, 12V input types	10.8	12	13.2	
Reflected ripple current	5V input types		12	20	mA p-p
	12V input types		5	10	


ABSOLUTE MAXIMUM RATINGS			
Lead temperature 1.5mm from case for 10 seconds	300°C		
Internal power dissipation	300mW		
Input voltage V _{IN} , MEA05 types	7V		
Input voltage V _{IN} , MEA12 types	15V		

OUTPUT CHARACTERISTICS					
Parameter	Conditions	Min.	Тур.	Max.	Units
Rated Power	T _A =-40°C to 85°C			1	W
Voltage Set Point Accuracy	See tolerance envelope				
Line regulation	High V _{IN} to low V _{IN}		1.05	1.2	%/%

ISOLATION CHARACTERISTICS					
Parameter	Conditions	Min.	Тур.	Max.	Units
Isolation test voltage	Flash tested for 1 second	1000			VDC
Resistance	Viso= 1000VDC	10			GΩ

GENERAL CHARACTERISTICS					
Parameter	Conditions	Min.	Тур.	Max.	Units
Switching frequency	5V input types		60		kHz
	12V input types		70		

TEMPERATURE CHARACTERISTICS						
Parameter	Conditions	Min.	Тур.	Max.	Units	
Specification	All output types	-40		85	°C	
Storage		-50		125		
Case Temperature above	5V output types			20	U	
ambient	All other output types			20		
Cooling	Free air convection					




- 2. Calculated using MIL-HDBK-217F FN2 with nominal input voltage at full load.
- All specifications typical at TA=25°C, nominal input voltage and rated output current unless otherwise specified.








1kVDC Isolated 1W Dual Output DC/DC Converters





TECHNICAL NOTES

ISOLATION VOLTAGE

'Hi Pot Test', 'Flash Tested', 'Withstand Voltage', 'Proof Voltage', 'Dielectric Withstand Voltage' & 'Isolation Test Voltage' are all terms that relate to the same thing, a test voltage, applied for a specified time, across a component designed to provide electrical isolation, to verify the integrity of that isolation.

Murata Power Solutions MEA series of DC/DC converters are all 100% production tested at their stated isolation voltage. This is 1kVDC for 1 minute.

A question commonly asked is, "What is the continuous voltage that can be applied across the part in normal operation?"

For a part holding no specific agency approvals, such as the MEA series, both input and output should normally be maintained within SELV limits i.e. less than 42.4V peak, or 60VDC. The isolation test voltage represents a measure of immunity to transient voltages and the part should never be used as an element of a safety isolation system. The part could be expected to function correctly with several hundred volts offset applied continuously across the isolation barrier; but then the circuitry on both sides of the barrier must be regarded as operating at an unsafe voltage and further isolation/insulation systems must form a barrier between these circuits and any user-accessible circuitry according to safety standard requirements.

REPEATED HIGH-VOLTAGE ISOLATION TESTING

It is well known that repeated high-voltage isolation testing of a barrier component can actually degrade isolation capability, to a lesser or greater degree depending on materials, construction and environment. The MEA series has toroidal isolation transformers, with no additional insulation between primary and secondary windings of enameled wire. While parts can be expected to withstand several times the stated test voltage, the isolation capability does depend on the wire insulation. Any material, including this enamel (typically polyurethane) is susceptible to eventual chemical degradation when subject to very high applied voltages thus implying that the number of tests should be strictly limited. We therefore strongly advise against repeated high voltage isolation testing, but if it is absolutely required, that the voltage be reduced by 20% from specified test voltage.

This consideration equally applies to agency recognized parts rated for better than functional isolation where the wire enamel insulation is always supplemented by a further insulation system of physical spacing or barriers.

Rohs Compliant Information



This series is compatible with RoHS soldering systems with a peak wave solder temperature of 300°C for 10 seconds. The pin termination finish on the SIP package type is Tin Plate, Hot Dipped over Matte Tin with Nickel Preplate. The DIP types are Matte Tin over Nickel Preplate. Both types in this series are backward compatible with Sn/Pb soldering systems.

For further information, please visit www.murata-ps.com/rohs


1kVDC Isolated 1W Dual Output DC/DC Converters

RIPPLE & NOISE CHARACTERISATION METHOD


All measurement to be taken with the following components connected to the UUT as detailed below.


50 Ohm coax cable, solder connections one end, BNC plug at the other end.

- $-1\mu F$ X7R multilayer ceramic capacitor rated at minimum 3 x the output voltage of the UUT
- C2 $-10\mu\text{F}$ tantalum capacitor rated at minimum 1.5 x the output voltage of the UUT with ESR of less than 100 milliohms at 100 kHz e.g. AVX TPS series.
- C3 100nF multilayer ceramic capacitor, general purpose
- R1 -450 Ohm resistor, carbon film, $\pm 1\%$
- R2 50 Ohm BNC termination
- T1 -3T of the coax cable through a ferrite toroid eg Ferroxcube TN32/19/13-3E25
- RLOAD Resistive load at the UUT maximum rating. Connections via twisted wires.



EFFICIENCY VS LOAD





Ø 0.045 (1.15) 0.039 (1.00)


0.1 (2.54)


5 HOLES 0.00394 (0.1)

0.1 (2.54)



1kVDC Isolated 1W Dual Output DC/DC Converters





muRata Ps Murata Power Solutions

Murata Power Solutions, Inc.

11 Cabot Boulevard, Mansfield, MA 02048-1151 U.S.A. Tel: (508) 339-3000 (800) 233-2765 Fax: (508) 339-6356

www.murata-ps.com email: sales@murata-ps.com ISO 9001 & ISO 14001 REGISTERED

Murata Power Solutions, Inc. makes no representation that the use of its products in the circuits described herein, or the use of other technical information contained herein, will not infringe upon existing or future patent rights. The descriptions contained herein do not imply the granting of licenses to make, use, or sell equipment constructed in accordance therewith. Specifications are subject to change without notice.

© 2008 Murata Power Solutions, Inc. USA: Mansfield (MA), Tel: (508) 339 3000, email: sales@murata-ps.com Canada: Toronto, Tel: (866) 740 1232, email: toronto@murata-ps.com UK: Milton Keynes, Tel: +44 (0)1908 615232, email: mk@murata-ps.com

Montigny Le Bretonneux, Tel: +33 (0)1 34 60 01 01, email: france@murata-ps.com France:

München, Tel: +49 (0)89-544334-0, email: ped.munich@murata-ps.com Germany: Tokyo, Tel: 3-3779-1031, email: sales_tokyo@murata-ps.com Japan:

Osaka, Tel: 6-6354-2025, email: sales_osaka@murata-ps.com

Shanghai, Tel: +86 215 027 3678, email: shanghai@murata-ps.com China: Guangzhou, Tel: +86 208 221 8066, email: guangzhou@murata-ps.com

Singapore: Parkway Centre, Tel: +65 6348 9096, email: singapore@murata-ps.com